

# RETROFIT LED DOWNLIGHTER

www.ringtail.co.uk - +44 (0) 1772 336335 - sales@ringtail.co.uk

**Ringtail**  
Lighting



A single LED and remote battery pack for easy conversions. This unit is the ultimate in concealed emergency lighting and suitable for incorporation into an emergency lighting system complying with BS5266-1:2005.

The FLC3NM is a complete solution to convert fluorescent downlights and decorative luminaires into emergency. Designed as a stand alone unit that fits discretely into most luminaires complete with 110° beam angle for optimum coverage with the ability adjust the angle for optimum light coverage.

This discrete LED downlight is both the emergency light output and charge indicator and should be used in non-maintained mode only. Consisting of a module, battery pack and LED unit these components fit together with non-reversible connectors. Once secured to the reflector and angled correctly the cable is passed through the lamp cut out and connected to the module.

## Technical Specification



	Mode	Lamp	Power Con	Battery	Duration	Weight	Emerg Output
FLC3NM	Non Maintained	3W LED	6.4VA	3.6V 4Ah NiCd	3 Hours	0.68 Kg	85 Lumens

- Quick and easy conversion
- Concealed emergency lighting
- Retro fit on-site
- White High Output LED light source
- Status Indicator LED

## Dimensions

