

HISPEC

LIGHTING • FIRE & CO DETECTION



110V

MODEL: HSLEDFLKIT/20M

INDUS LED FESTOON KIT

MAIN FEATURES:

- 20 metre chain
- 10 LED Lamps
- Plug and Coupler Fittings
- 2 metre spacing between light modules
- 6400k
- IP44 Rated
- Easy to install
- 2 year guarantee

SPECIFICATION

Input Voltage:	AC100-130V 50/60Hz
Bulb Type:	4W SMD LED x 10
Safety Level:	Class II
Lamp Lumens:	10 x 380Lm
Color Temperature:	6400K
Lamp Light Angle:	180°
LED Life Time:	30000hrs
Plug & Coupler Type:	16A 110V BS EN60309 IP44
Power Cord Length:	2Mtr Spacing Between Light Modules
Cable:	H05VV-F 2x0.75mm2 x 20Mtr
IP Rating:	IP44
Working Ambient Temperature:	-20°C-55°C
Linkable Quantity:	10 Units Maximum

IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS AND CAUTION. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. PLEASE KEEP INSTRUCTIONS SAFE FOR FUTURE USE.

INSTALLATION

Please ensure that you read the instructions before using the LED light and that all the safety guidelines are understood. Please keep these instruction for future reference.

- User should check the lamp body and lens carefully before use.
- Always check that the voltage displayed on the rating plate is the same as the mains power source.
- Prior to operation, carefully inspect the light for any damage. Any part that is damaged, including the casing, cable or plug, should be properly and safely repaired or replaced by a qualified electrician before the light is used.
- Ensure the cable is positioned to avoid presenting a trip hazard.
- Do not exceed the rated power loading for each type of lamp.
- Designed and manufactured to the highest of standards to ensure a robust and long life, we hope it provides you with many years of trouble-free, safe and reliable service. It is suitable for both indoor and outdoor operation.

IMPORTANT SAFETY INSTRUCTIONS

This instruction booklet contains vital information for the safe use and operation of the Festoon Kit, carefully read and understand all instructions before use. Failure to adhere to the instructions could result in serious personal injury or property damage. In addition, you should follow all warnings and instructions affixed to your Festoon Kit. This product has been carefully designed for its intended purpose and must not be modified in anyway. Any alteration may compromise safety, as well as invalidate Technical Production Approvals and your insurance.

IMPORTANT SAFETY INSTRUCTIONS

The Festoon Kit Lighting is designed and manufactured to robust standards. Correctly installed it is suitable for both internal and external use.

- On unpacking the Festoon it should be inspected for any damage.
- The installation should be entrusted to a competent person who if in doubt, must refer to a qualified electrical engineer.
- Any alterations may invalidate product approvals and your insurance.
- Check electrical cable for damage/abrasions before each usage.
- Do not illuminate when in a coil or enclose.

ELECTRICAL DATA

The Festoon is for use with a 110 volt supply only. The colour coded wires are brown for live, blue for neutral.

INSTALLATION

Do not connect to the power source until the Festoon is fully fitted into position. The first bulb holder module should be positioned to provide adequate cable length to the supply point, and should be suitably secured by strapping or similar restraint. Where practical each bulb holder module should be held in position, fixing holes are provided. When not practical it is recommended that a cable tie is used on each side of the module. Connection to the power source must be done with care. Ensure no personnel are in contact with the Festoon and switch on. Immediately check each bulb holder module to satisfy that no danger is present. Disconnect the Festoon from the power supply before removing or moving the Festoon Protect power cord from contact with sharp objects, chemicals or hot surfaces. Do not remove plug from mains supply by pulling on power cord. It is not recommended to connect directly with additional festoons, should this be done it should only be carried out by a qualified electrician.

MAINTENANCE

A daily check is recommended to inspect for any physical damage or abrasions to the power cables. Ensure there is no visible damage to the Festoon and that all connections to the power source are good.

FESTOON KIT CONTENT

20Mtr Chain With 10pcs LED lamps, Plug & Coupler Fittings and 20 cable ties.



This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

HISPEC
FIRE AND CO DETECTION

LOOKING FOR FIRE & CO PROTECTION FOR YOUR HOME?



SMOKE ALARMS

HEAT ALARMS

CARBON MONOXIDE DETECTORS

CHECK OUT OUR FULL RANGE OF FIRE & CO DETECTION PRODUCTS!

HISPEC.CO.UK